

# Injectronics

Remanufactured Automotive Electronics Components

## TECHNICAL BULLETIN

**Document number: T0087**

*For further technical information regarding testing, repairs or to search for New or Remanufactured Automotive electronic products, please visit [www.injectronics.com.au](http://www.injectronics.com.au), call our office on (+613) 8792 6999, or email [sales@injectronics.com.au](mailto:sales@injectronics.com.au)*

**Make: Mitsubishi**

**Model: Magna TE V6**

**Subject: Erratic idle**

The Injectronics technical department have had recent enquires regarding Mitsubishi TE V6 Magna, which have an erratic idle after having disconnecting the battery for whatever work was required. Since investigating the matter it has been found that there is a reset procedure to follow after reconnecting the battery to ensure that correct engine idle quality is obtained. Note: It is imperative that all lighting and ignition is turned off before disconnecting or reconnecting the battery. Bring engine to normal operating temperature and allow it to idle for approximately 10 minutes under the following conditions to help stabilise engine control conditions and then check idle quality is satisfactory.

1. Engine coolant temp 85-95°C
2. Lights off
3. Engine cooling fans off
4. Accessories off
5. Trans in park or neutral
6. Steering wheel in centre position

**T0087.doc**

This publication is distributed with the understanding that the authors, editors and publishers are not responsible for the results of any actions or works of whatsoever kind undertaken on the basis of information contained in this publication, nor for any errors or omissions contained herein. The publishers, authors and editors expressly disclaim all and any liability to any person whomsoever whether a purchaser of this publication or not in respect of anything and of the consequences of anything done or omitted to be done by any such persons in reliance, whether whole or partial upon the whole or any part of the contents of this publication. Injectronics Australia Pty Ltd. © Copyright 2001.